

## PRODUCT DATA

### NOISEBETA EAR PLUGS (CORDED, RE-USABLE) - MODEL 6080

#### INSTRUCTIONS FOR USE

NOISEBETA 6080 Ear Plug hearing protection must be properly worn to provide effective protection. Follow these instructions and contact the supplier where needed.

It is recommended that the wearer should ensure that:

- The Ear Plugs are fitted, adjusted and maintained in accordance with manufacturer's instructions.
- The Ear Plugs are worn at all times in noisy surroundings.
- The Ear Plugs are regularly inspected for serviceability.

#### WARNINGS

These Ear Plugs should not be used where there is a risk that the interconnecting cord could be caught up during use.

It is important that the fitting instructions and recommendations are adhered, if not, the protection afforded will be severely impaired.

This product may be adversely affected by certain chemical substances. Further information should be sought from the manufacturer.

Keep away from small children, [risk of inhalation and suffocation].

#### FITTING INSTRUCTIONS

Ear Plugs must be put in before exposure to noise and should be worn at all times in noisy environment.

- Gently pull the ear upward and backward.
- Hold the stem of the Ear Plug and insert well into the ear canal.
- Press slowly, with a twisting motion, to gradually obtain a seal.
- After use, remove Ear Plug slowly, and with a twisting motion, to gradually break the seal. Rapid removal may damage the ear drum.

Horizon House, Estate Road Five, Grimsby, DN31 2TG, United Kingdom

• +44 (0)8455 444 000 • sales@betafit.com • www.betafit.com

## PRODUCT DATA

### NOISEBETA DETECTABLE EAR PLUGS (CORDED, RE-USABLE) - MODEL 6080

#### ATTENUATION VALUES

SNR=29dB H=29dB M=27dB L=24dB  
Nominal Diameter = 7-11

| Frequency (Hz)     | 63   | 125  | 250  | 500  | 1000 | 2000 | 4000 | 8000 |
|--------------------|------|------|------|------|------|------|------|------|
| Mean Attenuation   | 29.2 | 28.5 | 27.9 | 29.7 | 34.1 | 32.5 | 36.8 | 43.8 |
| Standard Deviation | 6.5  | 6.8  | 6.0  | 5.8  | 5.3  | 5.7  | 5.1  | 4.2  |
| Assumed Protection | 22.7 | 21.7 | 21.9 | 23.9 | 28.8 | 26.7 | 31.7 | 39.6 |

Assumed Protection rounded to one decimal place.

**NOTE:** Tested According To BS EN 352-2:2002.

#### STORAGE & MAINTENANCE

This product must be stored in a dry, clean uncontaminated environment before and after use.


To maintain the Ear Plug in optimum condition it is recommended that they be cleaned regularly in lukewarm mild soapy water and dried with a soft cloth, without undue rubbing.

Disinfection: Use 95% Surgical Spirit to wipe the Ear Plugs.

This equipment is for personal use and should not be shared by different operators.

**CAUTION:** Whilst every effort is made to ensure the material, which comes into contact with wearer's skin, does not cause an allergic reaction, this may not be the case for a minority of susceptible individuals. In the event of any such problem, stop wearing the ear protector immediately and seek professional advice.

#### **FOR FURTHER INFORMATION CONTACT YOUR LOCAL DISTRIBUTOR:**



Horizon House, Estate Road Five, Grimsby, DN31 2TG, United Kingdom  
• +44 (0)8455 444 000 • sales@betafit.com • www.betafit.com